



▶ 2024

NEW PRODUCTS
MARSROCK



10000W~200000W

Three-phase IGBT

Low Frequency Inverter



► Product Specifications

	Rated Power	10kW	20kW	30kW	50kW	60kW	80kW	100kW	150kW	200kW
AC Input	Phase	Three Phase N+G								
	Voltage	AC220V/AC380V±20%								
	Frequency	50Hz/60Hz±5%								
DC Input	DC Voltage	DC(192V/220V/240V/384V)				DC384V				
	Floating Battery	13.6V of each battery x battery quantity [13.6V x 16 batteries =217.6V]								
	Cut-off Voltage	10.8V of each battery x battery quantity [10.8V x 16 batteries =172.8V]								
AC Output	Phase	Three phase N+G								
	Voltage	AC220V/AC380V±1% (steady load)								
	Efficiency	≥90% (Load100%)								
	Output Wave Form	Sine Wave								
	Dynamic Load Voltage	< +5%(From 0 to 100%)								
	Instant Recovery Time	<100ms								
	Unbalanced Voltage	< ±3% <±1% (Unbalanced load voltage)								
	Overload	120%,20s; >150%,100ms				125%,20s;>150%,1s				
	Working Efficiency	≥90%(Load:100%)								
	Computer Communication	RS232/485(SNMP Remote Monitoring Network Adapters)								
	Operating Temperature	-10°C~40°C								
Size(mm)	580*750*920			608*728*1475		1138*795*1725		1138*945*1725		
Weight(kg)	180	220	300	470	620	680	730	954	980	

MARS ROCK

Xiamen, P.R China



Tel: +86 5922237280
Mob: +86 18059289868
Web: www.marsrock.com.cn
marsrock@marsrock.com.cn